

Product Identification




Fig. 1 Delta




Fig. 2 BAPI-2




Fig. 3 Powers




Fig. 4 Precon

Mounting

#2 Phillips Screwdriver, 1/8" Screwdriver (BA116W), Minimum 22 Gauge Wire, Drill & Bits

Mounting




Fig. 5
Delta Style Room Unit Junction




Fig. 6
Powers (RSS) Style




Fig. 7
BAPI-Stat 2

Mounting hardware is provided for both junction box and drywall installation (junction box installation shown) for the Delta and BAPI-Stat 2 room units. Mounting hardware is provided for only the drywall installation of the Powers style room unit. Junction Box installation of the Powers style room unit will require a BAPI Adaptor Plate. Order Part Number **BA/ADP-525-7-Color Code**.

JUNCTION BOX INSTRUCTIONS

1. Pull the wire through the wall and out of the junction box, leaving about six inches free.
2. Pull the wire through the hole in the base plate.
3. Secure the base to the box using the # 6-32 x 3/4 inch mounting screw provided.
4. Terminate the unit according to the guidelines in **Termination** on page 2.
5. Attach Cover by latching it to the top of the base, rotating the cover down and snapping it into place.
6. For Delta, Precon and BAPI-Stat 2 units, secure the cover by backing out the lock-down screws using a 1/16" Allen wrench until they are flush with the bottom of the cover. For Powers(RSS) units, secure the cover by tightening the side security screws with a 1/16" Allen wrench.

(Drywall Mounting Instructions are found on page 2)

Specifications subject to change without notice.

Mounting Continued

DRYWALL MOUNTING INSTRUCTIONS

1. Place the base plate against the wall where you want to mount the sensor.
2. Using a pencil mark out the two mounting holes and the area where the wires will come through the wall.
3. Drill two 3/16" holes in the center of each marked mounting hole. Insert a drywall anchor into each hole.
4. Drill one 1/2" hole in the middle of the marked wiring area.
5. Pull the wire through the wall and out of the 1/2" hole, leaving about six inches free.
6. Pull the wire through the hole in the base plate.
7. Secure the base to the drywall anchors using the #6 x 1 inch mounting screws provided.
8. Terminate the unit according to the guidelines in **Termination** on page 2.
9. Attach Cover by latching it to the top of the base, rotating the cover down and snapping it into place.
10. For Delta, Precon and BAPI-Stat 2 units, secure the cover by backing out the lock-down screws using a 1/16" Allen wrench until they are flush with the bottom of the cover. For Powers (RSS) units, secure the cover by tightening the side security screws with a 1/16" Allen wrench.

NOTE: In a wall-mount application, the wall temperature and the temperature of the air within the wall cavity can cause erroneous readings. The mixing of room air and air from within the wall cavity can lead to condensation, erroneous readings and premature failure of the sensor. To prevent these conditions, seal the conduit leading to the junction box and seal the hole in the drywall by using an adhesive backed, foam insulating pad (order part number BA/FOAMBACK-ROOM).

Termination




Fig 8:
Delta and BAPI-Stat2 Enclosures




Figure 9:
Powers (RSS) Enclosure

Sensor Termination

Pin 1.... Sensor, To Analog Input of Controller (Resistive Output)

Pin 2.... Sensor, To Analog Input of Controller (Resistive Output)

Pin 3.... Not Used

NOTE: Sensor output tables are available on our website, www.bapihvac.com, or from your BAPI Representative.



BAPI recommends using twisted pair of at least 22AWG and sealant filled connectors for all wire connections. Larger gauge wire may be required for long runs. All wiring must comply with the National Electric Code (NEC) and local codes.

Do NOT run this device's wiring in the same conduit as AC power wiring of NEC class 1, NEC class 2, NEC class 3 or with wiring used to supply highly inductive loads such as motors, contactors and relays. BAPI's tests show that fluctuating and inaccurate signal levels are possible when AC power wiring is present in the same conduit as the signal lines. If you are experiencing any of these difficulties, please contact your BAPI representative



BAPI does not recommend wiring the sensor with power applied as accidental arcing may damage the product and will void the warranty

Diagnostics

POSSIBLE PROBLEMS:

General troubleshooting

Temperature reading is incorrect

POSSIBLE SOLUTIONS:

- Determine that the input is set up correctly in the controller software and building automation software.
- Check wiring for proper termination
- Check for corrosion at either the controller or the sensor. Clean off the corrosion, re-strip the interconnecting wire and reapply the connection. In extreme cases, replace the controller, interconnecting wire and/or sensor.
- Label the terminals that the interconnecting wires are connected to at the sensor end and the controller end. Disconnect the interconnecting wires from the controller and the sensor. With the interconnecting wires separated at both ends measure the resistance from wire-to-wire with a multimeter. The meter should read greater than 10 Meg-ohms, open or OL depending on the meter you have. Short the interconnecting wires together at one end. Go to the other end and measure the resistance from wire-to-wire with a multimeter. The meter should read less than 10 ohms (22 gauge or larger, 250 feet or less). If either test fails, replace the wire.
- Determine that the temperature sensors wires are connected to the correct controller input terminals and are not loose.
- Check the wires at the sensor for proper connections.
- Measure the physical temperature at the temperature sensor's location using an accurate temperature standard. Disconnect the temperature sensor wires and measure the temperature sensor's resistance across the sensor output pins with an ohmmeter. Compare the temperature sensor's resistance to the appropriate temperature sensor table on the BAPI web site. If the measured resistance is different from the temperature table by more than 5% call BAPI technical support. Find BAPI's web site at www.bapihvac.com; click on the button labeled SENSORS on the left of the screen and then click on the type of sensor you have. Don't forget to reconnect the wires.
- Make sure that the sensor leads are not touching one another.
- Determine if the sensor is exposed to an external air source different from room environment, such as a conduit draft. If so, fill the junction box with fiberglass insulation or plug the conduit.

Specifications subject to change without notice.