



Setpoint Output Range Options

				BAPI Room Units						
	Designator	Output Range	Span	Delta Style	R _μ P	R _μ PM	R _μ PS	BAPI-Stat	BAPI-Stat 2	BAPI-Stat 2M
Volts	00	0 to 5 V	5 Volts	x	x	x	x	x	x	x
	01	1 to 5 V	4 Volts		x	x		x		x
	02	3.7 to 0.85 V	2.85 Volts		x	x		x		x
	03	5 to 0 V	5 Volts	x	x	x	x	x	x	x
	04	4.2 to 1.2 V	3 Volts	x				x	x	x
	10	0 to 10 V	10 Volts			x		x		x
Current	16	4-20 mA	16 mA					x		
<1kΩ Span	20	889 to 111 Ω	778Ω			x		x		x
	21	792 to 208 Ω	584Ω			x		x		x
	22	695 to 305 Ω	390Ω			x		x		x
	23	674 to 274 Ω	400Ω	x		x	x	x	x	x
	24	597 to 305 Ω	292Ω			x		x		x
	25	800 to 1200	400Ω	x		x	x	x	x	x
	26	909 to 1309	400Ω	x		x	x	x	x	x
	27	1800 to 2200	400Ω	x		x	x	x	x	x
	28	866 to 1286	400Ω	x		x	x	x	x	x
1kΩ Span	40	0 to 1 kΩ	1 kΩ	x		x	x	x	x	x
	41	500 to 1500 Ω	1 kΩ	x		x	x	x	x	x
	42	2 to 3 kΩ	1 kΩ	x		x	x	x	x	x
	43	249 to 1249 Ω	1 kΩ	x		x	x	x	x	x
	44	10 to 11 kΩ	1 kΩ	x			x	x	x	x
	45	12.5K-11.5K Ω	1 kΩ	x			x	x	x	x
	46	1K to 0 Ω	1 kΩ	x		x	x	x	x	x
	47	182 to 1182 Ω	1 kΩ	x		x	x	x	x	x
5kΩ Span	50	0 to 5 kΩ	5 kΩ	x		x		x	x	x
	51	7.87k to 2.87kΩ	5 kΩ	x		x		x	x	x
10kΩ Span	60	0 to 10 kΩ	10 kΩ	x	x	x	x	x	x	x
	61	15 to 5 kΩ	10 kΩ	x	x	x	x	x	x	x
	62	9577 to 1422 Ω			x	x		x		x
	63	1 to 11 kΩ	10 kΩ	x		x	x	x	x	x
20kΩ Span	80	0 to 20 kΩ	20 kΩ	x	x	x	x	x	x	x
	81	4.75 to 24.75 kΩ	20 kΩ	x	x	x	x	x	x	x
	82	6.19 to 26.19 kΩ	20 kΩ	x	x	x	x	x	x	x
	83	7.87 to 27.87 kΩ	20 kΩ	x	x	x	x	x	x	x
	84	10 to 30 kΩ	20 kΩ	x	x	x	x	x	x	x
	85	24.75 to 4.75 kΩ	20 kΩ	x	x	x	x	x	x	x

An "x" in the box indicates that the output range is available for that room unit.

Note: RuP and RupD options 60, 61 and 62 are not available for large display spans. Contact your BAPI representative for additional information.